

# Systeme anti-démarrage à code

## Anti-start code system

**G'TEL**

[www.g-tel.fr](http://www.g-tel.fr)



## SAD 1000

### Module de démarrage à code

- Clavier 12 touches
- Alimentation sur batterie 12 ou 24 Vcc (Plage de 6 à 40 Vcc)
- 3 niveaux de codes programmables
- Codes à 4, 5, ou 6 chiffres paramétrables
- Programmation de la temporisation entre 2 utilisations
- Mode ECO (veille paramétrable)
- Signalisation par 2 voyants LED
- Afficheur LED 7 segments
- 4 coupures 7,5 A
- Raccordement par câble et connecteur IP65
- Clavier face inox IP65 67x92x18 mm
- Poids : 810 g (kit complet)
- Installation en saillie sans vis apparentes

### Anti-start code module

- 12 keys keypad
- Battery supply 12 or 24 Vcc (from 6 to 40 Vcc)
- 3 levels of activation
- Codes 4 to 6-digit (customizable)
- Stop time delay between 2 utilizations (programmable)
- ECO mode (configurable standby)
- 2 LED indicators
- 7 segments LED display
- 4 cuts 7,5 A
- Connection by cable and connector IP65
- Stainless face case IP65 67x92x18 mm
- Weight : 810 g (complete kit)
- Installation in projection without visible crews

 **GAROS**  
Electronique  
HIGH LEVEL SERVICE